

**Adaptor 1.35mm-Female to 1.85mm-Female****135F-185F+***Typical Performance Data (+25°C)*

FREQ.	INSERTION LOSS	1.35mm-FEMALE VSWR	1.85mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.2	0.02	1.01	1.01
0.4	0.03	1.02	1.01
0.6	0.04	1.02	1.02
0.8	0.05	1.02	1.02
1.0	0.05	1.03	1.03
3.0	0.09	1.04	1.03
5.0	0.11	1.04	1.04
7.0	0.11	1.03	1.03
9.0	0.12	1.02	1.01
11.0	0.12	1.01	1.01
13.0	0.13	1.01	1.01
15.0	0.13	1.01	1.01
17.0	0.14	1.03	1.03
19.0	0.15	1.04	1.05
21.0	0.16	1.05	1.05
23.0	0.16	1.03	1.05
25.0	0.17	1.04	1.03
27.0	0.17	1.02	1.03
29.0	0.17	1.01	1.02
31.0	0.17	1.02	1.02
33.0	0.17	1.04	1.03
35.0	0.18	1.04	1.05
37.0	0.19	1.07	1.07
39.0	0.19	1.06	1.08
41.0	0.20	1.05	1.08
43.0	0.20	1.01	1.03
45.0	0.21	1.02	1.02
47.0	0.22	1.04	1.03
49.0	0.23	1.01	1.04
51.0	0.23	1.03	1.03
53.0	0.24	1.02	1.02
55.0	0.24	1.04	1.05
57.0	0.25	1.04	1.05
59.0	0.27	1.06	1.04
61.0	0.30	1.04	1.04
63.0	0.30	1.04	1.07
65.0	0.29	1.07	1.08
67.0	0.27	1.03	1.05



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS

REV. OR  
 135F-185F+  
 6/11/2024  
 Page 1 of 1