

Adaptor 1.35mm-Male to 1.85mm-Female**135M-185F+***Typical Performance Data (+25°C)*

FREQ.	INSERTION LOSS	1.35mm-MALE VSWR	1.85mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.2	0.02	1.01	1.01
0.4	0.03	1.01	1.02
0.6	0.04	1.02	1.02
0.8	0.05	1.02	1.03
1.0	0.05	1.02	1.03
3.0	0.08	1.04	1.04
5.0	0.10	1.04	1.04
7.0	0.11	1.03	1.03
9.0	0.11	1.02	1.02
11.0	0.11	1.01	1.03
13.0	0.11	1.01	1.03
15.0	0.12	1.01	1.03
17.0	0.12	1.01	1.04
19.0	0.13	1.03	1.06
21.0	0.14	1.07	1.08
23.0	0.14	1.05	1.08
25.0	0.14	1.06	1.05
27.0	0.14	1.02	1.03
29.0	0.14	1.02	1.02
31.0	0.15	1.03	1.05
33.0	0.16	1.06	1.07
35.0	0.16	1.08	1.08
37.0	0.17	1.10	1.09
39.0	0.17	1.08	1.08
41.0	0.18	1.07	1.05
43.0	0.18	1.03	1.07
45.0	0.20	1.06	1.12
47.0	0.20	1.04	1.11
49.0	0.20	1.02	1.08
51.0	0.20	1.05	1.09
53.0	0.21	1.04	1.07
55.0	0.21	1.05	1.05
57.0	0.23	1.08	1.07
59.0	0.25	1.07	1.08
61.0	0.27	1.05	1.08
63.0	0.27	1.07	1.09
65.0	0.26	1.10	1.07
67.0	0.27	1.05	1.07



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
 135M-185F+
 5/15/2024
 Page 1 of 1