

Adapter 1.85mm-Male to 1.85mm-Male**185MR-185M+***Typical Performance Data*

FREQ.	INSERTION LOSS	1.85mm-MALE VSWR	1.85mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.00	1.01
0.50	0.01	1.01	1.01
0.80	0.02	1.01	1.01
1.00	0.02	1.01	1.01
3.00	0.04	1.02	1.02
5.00	0.06	1.02	1.02
7.00	0.07	1.06	1.06
9.00	0.08	1.10	1.10
11.00	0.09	1.12	1.12
13.00	0.09	1.14	1.14
15.00	0.11	1.10	1.11
17.00	0.11	1.06	1.09
19.00	0.13	1.05	1.07
21.00	0.14	1.11	1.13
23.00	0.16	1.18	1.17
25.00	0.18	1.17	1.18
27.00	0.16	1.11	1.12
29.00	0.16	1.05	1.03
31.00	0.19	1.16	1.15
33.00	0.26	1.29	1.28
35.00	0.29	1.29	1.30
37.00	0.25	1.20	1.24
39.00	0.21	1.06	1.11
41.00	0.22	1.10	1.08
43.00	0.24	1.15	1.10
45.00	0.25	1.22	1.18
47.00	0.26	1.24	1.24
49.00	0.29	1.31	1.30
51.00	0.27	1.23	1.22
53.00	0.24	1.11	1.12
55.00	0.25	1.11	1.12
57.00	0.26	1.18	1.15
59.00	0.28	1.26	1.18
61.00	0.28	1.28	1.17
63.00	0.27	1.18	1.12
65.00	0.35	1.26	1.16
67.00	0.39	1.18	1.24



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
185MR-185M+
10/31/2025
Page 1 of 1