

Adapter, 1.85 mm-Male Right-Angle to 2.4 mm-Male

185MR-24M+

Typical Performance Data

FREQ.	INSERTION LOSS	1.85 mm-MALE VSWR	2.4 mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0	0.01	1.02	1.02
1	0.03	1.02	1.02
2	0.04	1.03	1.04
3	0.05	1.04	1.04
4	0.04	1.04	1.04
5	0.05	1.03	1.03
6	0.05	1.02	1.02
7	0.05	1.02	1.02
8	0.05	1.05	1.05
9	0.06	1.09	1.09
10	0.06	1.12	1.11
11	0.07	1.13	1.13
12	0.08	1.15	1.16
13	0.08	1.16	1.16
14	0.08	1.13	1.13
15	0.07	1.08	1.09
16	0.06	1.04	1.05
17	0.07	1.04	1.05
18	0.07	1.10	1.10
19	0.10	1.17	1.17
20	0.11	1.23	1.22
21	0.12	1.25	1.25
22	0.13	1.25	1.25
23	0.12	1.23	1.23
24	0.11	1.17	1.17
25	0.09	1.10	1.10
26	0.09	1.04	1.04
27	0.09	1.05	1.04
28	0.10	1.07	1.07
29	0.11	1.12	1.13
30	0.13	1.19	1.21
31	0.16	1.23	1.27
32	0.13	1.19	1.22
33	0.13	1.14	1.14
34	0.11	1.07	1.08
35	0.10	1.06	1.06
36	0.11	1.10	1.10
37	0.12	1.10	1.12
38	0.12	1.10	1.10
39	0.11	1.06	1.06
40	0.12	1.03	1.03
41	0.12	1.05	1.03
42	0.12	1.08	1.05
43	0.15	1.14	1.12
44	0.17	1.21	1.21
45	0.16	1.24	1.24
46	0.16	1.12	1.13
47	0.15	1.05	1.03
48	0.15	1.05	1.05
49	0.15	1.04	1.05
50	0.20	1.15	1.18



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
185MR-24M+
10/21/2025
Page 1 of 1