

Adapter 2.92mm-Female to 3.5mm-Female

KFR-35F+

Typical Performance Data

FREQ.	INSERTION LOSS	2.92mm-FEMALE VSWR	3.5mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.01
0.10	0.01	1.00	1.00
0.20	0.02	1.01	1.01
0.30	0.02	1.01	1.01
0.40	0.03	1.01	1.01
0.50	0.03	1.01	1.01
0.60	0.03	1.01	1.02
0.70	0.04	1.02	1.02
0.80	0.04	1.02	1.02
0.90	0.04	1.02	1.02
1.00	0.04	1.02	1.02
2.00	0.05	1.04	1.04
3.00	0.06	1.04	1.04
4.00	0.06	1.04	1.03
5.00	0.06	1.02	1.02
6.00	0.07	1.01	1.01
7.00	0.07	1.03	1.03
8.00	0.08	1.06	1.07
9.00	0.08	1.09	1.09
10.00	0.09	1.11	1.11
11.00	0.09	1.12	1.12
12.00	0.09	1.11	1.11
13.00	0.10	1.10	1.10
14.00	0.09	1.07	1.08
15.00	0.09	1.04	1.05
16.00	0.10	1.02	1.04
17.00	0.11	1.03	1.04
18.00	0.11	1.06	1.06
19.00	0.12	1.08	1.08
20.00	0.13	1.10	1.10
21.00	0.13	1.11	1.11
22.00	0.14	1.12	1.12
23.00	0.14	1.11	1.11
24.00	0.15	1.11	1.10
25.00	0.15	1.11	1.10
26.00	0.16	1.10	1.09
27.00	0.15	1.09	1.08
28.00	0.15	1.07	1.07
29.00	0.16	1.05	1.05
30.00	0.16	1.04	1.04
31.00	0.16	1.02	1.03
32.00	0.17	1.03	1.02
33.00	0.18	1.04	1.03



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
KFR-35F+
12/5/2025
Page 1 of 1