

# Adapter 2.92mm-Male to 3.5mm-Female

# KMR-35F+

## Typical Performance Data

FREQ.	INSERTION LOSS	2.92mm-MALE VSWR	3.5mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.00	1.00
0.10	0.01	1.01	1.01
0.20	0.02	1.01	1.01
0.30	0.03	1.01	1.01
0.40	0.03	1.01	1.01
0.50	0.03	1.01	1.01
0.60	0.04	1.02	1.02
0.70	0.04	1.02	1.02
0.80	0.04	1.02	1.02
0.90	0.04	1.02	1.02
1.00	0.04	1.02	1.02
2.00	0.05	1.04	1.04
3.00	0.06	1.04	1.04
4.00	0.06	1.02	1.02
5.00	0.07	1.01	1.01
6.00	0.07	1.03	1.03
7.00	0.08	1.06	1.06
8.00	0.09	1.10	1.10
9.00	0.10	1.13	1.13
10.00	0.10	1.13	1.13
11.00	0.10	1.11	1.12
12.00	0.10	1.08	1.08
13.00	0.10	1.05	1.04
14.00	0.10	1.02	1.02
15.00	0.11	1.06	1.06
16.00	0.12	1.11	1.11
17.00	0.14	1.14	1.16
18.00	0.15	1.16	1.17
19.00	0.15	1.16	1.17
20.00	0.15	1.15	1.15
21.00	0.15	1.12	1.11
22.00	0.15	1.08	1.07
23.00	0.15	1.04	1.03
24.00	0.15	1.02	1.02
25.00	0.15	1.04	1.04
26.00	0.16	1.07	1.07
27.00	0.17	1.10	1.10
28.00	0.18	1.11	1.11
29.00	0.19	1.13	1.11
30.00	0.19	1.14	1.12
31.00	0.20	1.12	1.11
32.00	0.19	1.09	1.09
33.00	0.19	1.06	1.06



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR  
 KMR-35F+  
 12/5/2025  
 Page 1 of 1