

Adaptor 1.0mm-Female to 1.35mm-Male**10F-135M+***Typical Performance Data (+25°C)*

FREQ.	INSERTION LOSS	1.0mm-FEMALE VSWR	1.35mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.6	0.04	1.02	1.02
1.0	0.06	1.03	1.03
4.0	0.11	1.05	1.06
7.0	0.14	1.04	1.05
10.0	0.14	1.02	1.01
13.0	0.14	1.05	1.04
16.0	0.15	1.06	1.06
19.0	0.15	1.03	1.04
22.0	0.16	1.05	1.05
25.0	0.18	1.09	1.09
28.0	0.19	1.10	1.09
31.0	0.20	1.06	1.04
34.0	0.21	1.06	1.05
37.0	0.22	1.06	1.07
40.0	0.22	1.05	1.05
43.0	0.25	1.07	1.03
46.0	0.26	1.10	1.04
49.0	0.27	1.07	1.03
52.0	0.28	1.02	1.02
55.0	0.30	1.04	1.05
58.0	0.31	1.06	1.07
61.0	0.32	1.05	1.04
64.0	0.34	1.08	1.08
67.0	0.37	1.12	1.15
70.0	0.39	1.09	1.13
73.0	0.40	1.03	1.09
76.0	0.41	1.05	1.06
79.0	0.43	1.10	1.09
82.0	0.44	1.07	1.08
85.0	0.44	1.04	1.03
88.0	0.46	1.09	1.12
90.0	0.48	1.09	1.11



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS