

Adaptor 1.0mm-Male to 1.35mm-Female**10M-135F+***Typical Performance Data (+25°C)*

FREQ.	INSERTION LOSS	1.0mm-MALE VSWR	1.35mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.6	0.05	1.03	1.03
1.0	0.07	1.04	1.04
4.0	0.12	1.10	1.09
7.0	0.14	1.09	1.09
10.0	0.15	1.03	1.03
13.0	0.16	1.02	1.04
16.0	0.17	1.04	1.04
19.0	0.19	1.02	1.02
22.0	0.20	1.05	1.06
25.0	0.23	1.10	1.11
28.0	0.23	1.09	1.11
31.0	0.23	1.07	1.07
34.0	0.25	1.05	1.03
37.0	0.26	1.09	1.07
40.0	0.26	1.08	1.05
43.0	0.28	1.06	1.04
46.0	0.29	1.04	1.04
49.0	0.32	1.04	1.03
52.0	0.32	1.05	1.04
55.0	0.34	1.07	1.08
58.0	0.34	1.05	1.07
61.0	0.38	1.06	1.05
64.0	0.39	1.07	1.06
67.0	0.39	1.15	1.12
70.0	0.40	1.12	1.09
73.0	0.41	1.06	1.04
76.0	0.43	1.08	1.12
79.0	0.44	1.10	1.14
82.0	0.45	1.04	1.12
85.0	0.51	1.07	1.04
88.0	0.53	1.15	1.08
90.0	0.56	1.20	1.10



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
 10M-135F+
 6/7/2024
 Page 1 of 1