

Adaptor 1.0mm-Male to 1.35mm-Male**10M-135M+***Typical Performance Data (+25°C)*

FREQ.	INSERTION LOSS	1.0mm-MALE VSWR	1.35mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.6	0.04	1.02	1.02
1.0	0.06	1.02	1.02
4.0	0.11	1.02	1.03
7.0	0.14	1.01	1.02
10.0	0.15	1.03	1.01
13.0	0.16	1.03	1.02
16.0	0.16	1.05	1.02
19.0	0.17	1.06	1.04
22.0	0.18	1.06	1.05
25.0	0.20	1.06	1.06
28.0	0.20	1.07	1.06
31.0	0.22	1.08	1.08
34.0	0.23	1.09	1.09
37.0	0.23	1.04	1.07
40.0	0.25	1.04	1.02
43.0	0.27	1.09	1.02
46.0	0.28	1.10	1.04
49.0	0.30	1.09	1.04
52.0	0.31	1.09	1.05
55.0	0.32	1.06	1.03
58.0	0.33	1.05	1.05
61.0	0.34	1.03	1.06
64.0	0.35	1.02	1.05
67.0	0.38	1.07	1.02
70.0	0.41	1.15	1.08
73.0	0.43	1.13	1.09
76.0	0.44	1.09	1.03
79.0	0.46	1.07	1.07
82.0	0.47	1.12	1.11
85.0	0.50	1.16	1.14
88.0	0.51	1.15	1.09
90.0	0.49	1.09	1.08



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
 10M-135M+
 6/7/2024
 Page 1 of 1