

Torque Nut Adapter 2.4 mm Male to 2.4 mm Male

24M-24M-T+

Typical Performance Data

FREQ.	INSERTION LOSS	2.4 mm MALE VSWR	2.4 mm MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0	-0.01	1.02	1.02
1	-0.03	1.02	1.02
2	-0.05	1.04	1.04
3	-0.06	1.05	1.05
4	-0.07	1.06	1.06
5	-0.07	1.06	1.06
6	-0.08	1.05	1.05
7	-0.08	1.03	1.04
8	-0.09	1.02	1.02
9	-0.09	1.01	1.01
10	-0.10	1.01	1.01
11	-0.10	1.01	1.01
12	-0.11	1.02	1.01
13	-0.11	1.03	1.03
14	-0.12	1.05	1.05
15	-0.12	1.07	1.07
16	-0.13	1.08	1.09
17	-0.13	1.09	1.10
18	-0.14	1.09	1.10
19	-0.15	1.09	1.09
20	-0.14	1.08	1.08
21	-0.14	1.07	1.07
22	-0.15	1.05	1.05
23	-0.14	1.03	1.03
24	-0.15	1.02	1.01
25	-0.15	1.04	1.03
26	-0.16	1.05	1.03
27	-0.16	1.05	1.03
28	-0.16	1.04	1.04
29	-0.17	1.05	1.05
30	-0.17	1.07	1.07
31	-0.18	1.08	1.08
32	-0.19	1.10	1.10
33	-0.19	1.10	1.10
34	-0.19	1.09	1.10
35	-0.19	1.06	1.07
36	-0.20	1.03	1.04
37	-0.19	1.03	1.04
38	-0.19	1.06	1.07
39	-0.20	1.09	1.09
40	-0.21	1.08	1.09
41	-0.22	1.08	1.09
42	-0.22	1.08	1.06
43	-0.23	1.10	1.06
44	-0.21	1.10	1.05
45	-0.23	1.08	1.04
46	-0.22	1.04	1.02
47	-0.22	1.02	1.03
48	-0.24	1.06	1.05
49	-0.25	1.07	1.07
50	-0.25	1.09	1.09



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS