

Adaptor 2.4mm-Male to 3.5mm-Female**24M-35F+***Typical Performance Data*

FREQ.	INSERTION LOSS	2.4mm-MALE VSWR	3.5mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.02	1.02
0.10	0.01	1.00	1.00
0.20	0.01	1.00	1.01
0.30	0.02	1.00	1.01
0.40	0.02	1.00	1.01
0.50	0.02	1.00	1.01
0.60	0.03	1.00	1.01
0.70	0.03	1.00	1.02
0.80	0.03	1.00	1.02
1.00	0.03	1.00	1.02
2.00	0.04	1.01	1.03
3.00	0.04	1.02	1.03
4.00	0.05	1.02	1.02
5.00	0.05	1.03	1.03
6.00	0.06	1.04	1.04
7.00	0.06	1.05	1.06
8.00	0.06	1.06	1.06
9.00	0.06	1.06	1.06
10.00	0.06	1.06	1.06
11.00	0.07	1.06	1.06
12.00	0.08	1.06	1.07
13.00	0.08	1.07	1.05
14.00	0.08	1.06	1.02
15.00	0.08	1.07	1.03
16.00	0.09	1.07	1.08
17.00	0.09	1.07	1.11
18.00	0.09	1.05	1.12
19.00	0.09	1.05	1.11
20.00	0.10	1.06	1.09
21.00	0.11	1.09	1.08
22.00	0.11	1.11	1.07
23.00	0.11	1.13	1.05
24.00	0.11	1.12	1.01
25.00	0.13	1.09	1.06
26.00	0.13	1.05	1.12
27.00	0.14	1.04	1.18
28.00	0.15	1.06	1.20
29.00	0.15	1.09	1.16
30.00	0.15	1.11	1.09
31.00	0.14	1.12	1.02
32.00	0.15	1.11	1.07
33.00	0.16	1.10	1.12
34.50	0.17	1.12	1.12



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
24M-35F+
8/14/2025
Page 1 of 1