

Right Angle Torquing Adapter 2.4 mm Male to 2.4 mm Male

24MR-24M-T+

Typical Performance Data

FREQ.	INSERTION LOSS	2.4 mm MALE VSWR	2.4 mm MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0	0.00	1.17	1.17
1	-0.04	1.02	1.02
2	-0.06	1.04	1.03
3	-0.06	1.04	1.04
4	-0.07	1.03	1.02
5	-0.08	1.02	1.01
6	-0.09	1.05	1.05
7	-0.10	1.09	1.09
8	-0.11	1.13	1.13
9	-0.12	1.15	1.16
10	-0.13	1.17	1.17
11	-0.13	1.14	1.15
12	-0.12	1.11	1.11
13	-0.12	1.05	1.05
14	-0.12	1.02	1.01
15	-0.13	1.05	1.05
16	-0.14	1.10	1.10
17	-0.14	1.14	1.15
18	-0.16	1.16	1.19
19	-0.18	1.17	1.19
20	-0.17	1.16	1.18
21	-0.17	1.15	1.13
22	-0.17	1.11	1.09
23	-0.15	1.05	1.03
24	-0.16	1.05	1.06
25	-0.18	1.12	1.11
26	-0.20	1.19	1.18
27	-0.22	1.23	1.21
28	-0.22	1.21	1.21
29	-0.21	1.16	1.17
30	-0.21	1.12	1.12
31	-0.21	1.11	1.12
32	-0.23	1.16	1.17
33	-0.25	1.23	1.23
34	-0.28	1.27	1.27
35	-0.25	1.28	1.28
36	-0.28	1.23	1.23
37	-0.25	1.15	1.16
38	-0.25	1.09	1.10
39	-0.25	1.10	1.07
40	-0.26	1.10	1.07
41	-0.26	1.09	1.08
42	-0.27	1.07	1.10
43	-0.27	1.07	1.11
44	-0.28	1.12	1.13
45	-0.32	1.16	1.17
46	-0.34	1.23	1.21
47	-0.33	1.27	1.25
48	-0.34	1.19	1.20
49	-0.31	1.09	1.10
50	-0.28	1.06	1.06



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS