

# Adapter 2.4mm-Male to 3.5mm-Female

# 24MR-35F+

## Typical Performance Data

FREQ.	INSERTION LOSS	2.4mm-MALE VSWR	3.5mm-FEMALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.01
0.10	0.01	1.01	1.00
0.20	0.02	1.01	1.01
0.30	0.02	1.01	1.01
0.40	0.03	1.02	1.01
0.50	0.03	1.02	1.01
0.60	0.03	1.02	1.01
0.70	0.04	1.03	1.01
0.80	0.04	1.03	1.01
0.90	0.04	1.03	1.01
1.00	0.04	1.03	1.02
2.00	0.05	1.04	1.02
3.00	0.06	1.04	1.02
4.00	0.06	1.02	1.02
5.00	0.07	1.01	1.01
6.00	0.07	1.02	1.03
7.00	0.08	1.05	1.07
8.00	0.09	1.11	1.11
9.00	0.10	1.16	1.14
10.00	0.12	1.20	1.16
11.00	0.12	1.19	1.16
12.00	0.12	1.12	1.13
13.00	0.11	1.04	1.08
14.00	0.11	1.07	1.02
15.00	0.12	1.13	1.09
16.00	0.12	1.14	1.17
17.00	0.11	1.12	1.24
18.00	0.11	1.11	1.28
19.00	0.12	1.15	1.28
20.00	0.15	1.19	1.22
21.00	0.15	1.18	1.14
22.00	0.14	1.13	1.08
23.00	0.13	1.10	1.09
24.00	0.15	1.15	1.17
25.00	0.18	1.21	1.23
26.00	0.19	1.24	1.25
27.00	0.18	1.21	1.22
28.00	0.16	1.16	1.18
29.00	0.16	1.09	1.12
30.00	0.17	1.09	1.07
31.00	0.17	1.11	1.05
32.00	0.17	1.11	1.07
33.00	0.17	1.08	1.10



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS

REV. OR  
 24MR-35F+  
 12/5/2025  
 Page 1 of 1