

Non-Magnetic Flex Cable SMP Male to SMA Male

86N-50CSMPMSM

Typical Performance Data

FREQ.	INSERTION LOSS	SMP MALE VSSWR	SMA MALE VSSWR
(GHz)	(dB)	(dB)	(dB)
0.01	0.06	1.01	1.01
0.10	0.13	1.04	1.04
0.15	0.27	1.03	1.03
1.00	0.38	1.01	1.01
2.00	0.54	1.04	1.04
2.50	0.60	1.02	1.01
3.00	0.66	1.03	1.03
3.50	0.72	1.05	1.04
4.00	0.78	1.02	1.03
4.50	0.83	1.03	1.02
5.00	0.88	1.07	1.06
5.50	0.93	1.05	1.04
6.00	0.97	1.05	1.03
6.50	1.01	1.07	1.06
7.00	1.05	1.04	1.03
7.50	1.09	1.04	1.02
8.00	1.13	1.04	1.03
8.50	1.17	1.03	1.03
9.00	1.21	1.05	1.04
9.50	1.25	1.07	1.06
10.00	1.30	1.09	1.07
10.50	1.33	1.09	1.08
11.00	1.37	1.14	1.12
11.50	1.40	1.13	1.09
12.00	1.44	1.13	1.09
12.50	1.48	1.19	1.15
13.00	1.50	1.14	1.09
13.50	1.53	1.10	1.06
14.00	1.57	1.12	1.10
14.50	1.59	1.07	1.07
15.00	1.62	1.06	1.06
15.50	1.66	1.08	1.09
16.00	1.70	1.06	1.09
16.50	1.73	1.08	1.09
17.00	1.77	1.11	1.11
17.50	1.79	1.05	1.06
18.00	1.83	1.13	1.12



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
86N-50CSMPMSM
6/29/2026
Page 1 of 1