

Adapter 2.92mm-Female to 3.5mm-Male

KFR-35M+

Typical Performance Data

FREQ.	INSERTION LOSS	2.92mm-FEMALE VSWR	3.5mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.00	1.00
0.10	0.01	1.00	1.01
0.20	0.02	1.01	1.01
0.30	0.03	1.01	1.01
0.40	0.03	1.01	1.01
0.50	0.04	1.01	1.01
0.60	0.04	1.01	1.01
0.70	0.04	1.01	1.02
0.80	0.04	1.02	1.02
0.90	0.05	1.02	1.02
1.00	0.05	1.02	1.02
2.00	0.06	1.03	1.03
3.00	0.07	1.03	1.03
4.00	0.08	1.03	1.02
5.00	0.08	1.02	1.03
6.00	0.09	1.02	1.02
7.00	0.09	1.03	1.03
8.00	0.10	1.04	1.05
9.00	0.10	1.06	1.05
10.00	0.11	1.07	1.05
11.00	0.12	1.05	1.06
12.00	0.12	1.05	1.06
13.00	0.13	1.06	1.06
14.00	0.13	1.07	1.08
15.00	0.14	1.07	1.07
16.00	0.14	1.07	1.08
17.00	0.15	1.07	1.09
18.00	0.16	1.06	1.07
19.00	0.16	1.05	1.05
20.00	0.16	1.04	1.04
21.00	0.17	1.05	1.06
22.00	0.18	1.07	1.07
23.00	0.19	1.09	1.09
24.00	0.19	1.10	1.09
25.00	0.20	1.10	1.10
26.00	0.20	1.08	1.07
27.00	0.20	1.06	1.05
28.00	0.20	1.04	1.04
29.00	0.21	1.03	1.04
30.00	0.21	1.03	1.04
31.00	0.22	1.07	1.07
32.00	0.23	1.11	1.10
33.00	0.25	1.15	1.15



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com



IF/RF MICROWAVE COMPONENTS

REV. OR
 KFR-35M+
 12/5/2025
 Page 1 of 1