

Torque Nut Adapter 2.92 mm Male to 2.92 mm Male

KM-KM50-T+

Typical Performance Data

FREQ.	INSERTION LOSS	2.92 mm MALE VSWR	2.92 mm MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0	-0.01	1.01	1.01
1	-0.03	1.01	1.02
2	-0.04	1.02	1.02
3	-0.05	1.03	1.04
4	-0.06	1.04	1.04
5	-0.06	1.04	1.04
6	-0.06	1.04	1.04
7	-0.07	1.04	1.04
8	-0.07	1.04	1.03
9	-0.07	1.03	1.03
10	-0.07	1.03	1.02
11	-0.07	1.02	1.02
12	-0.08	1.02	1.02
13	-0.08	1.02	1.02
14	-0.08	1.02	1.02
15	-0.09	1.02	1.02
16	-0.09	1.02	1.02
17	-0.09	1.03	1.03
18	-0.10	1.03	1.03
19	-0.10	1.03	1.03
20	-0.10	1.04	1.04
21	-0.11	1.04	1.04
22	-0.11	1.03	1.03
23	-0.11	1.03	1.03
24	-0.11	1.03	1.02
25	-0.11	1.02	1.01
26	-0.11	1.02	1.02
27	-0.10	1.02	1.02
28	-0.10	1.02	1.03
29	-0.10	1.03	1.03
30	-0.09	1.04	1.03
31	-0.08	1.03	1.03
32	-0.08	1.02	1.04
33	-0.08	1.03	1.03
34	-0.08	1.04	1.02
35	-0.08	1.03	1.03
36	-0.09	1.02	1.03
37	-0.10	1.03	1.02
38	-0.10	1.02	1.02
39	-0.10	1.02	1.02
40	-0.12	1.05	1.04



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
KM-KM50-T+
12/9/2024
Page 1 of 1