

# Adapter 2.92mm-Male to 3.5mm-Male

# KMR-35M+

## Typical Performance Data

FREQ.	INSERTION LOSS	2.92mm-MALE VSWR	3.5mm-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.01
0.10	0.01	1.01	1.01
0.20	0.02	1.01	1.01
0.30	0.03	1.01	1.01
0.40	0.03	1.01	1.02
0.50	0.03	1.02	1.02
0.60	0.04	1.02	1.02
0.70	0.04	1.02	1.02
0.80	0.04	1.02	1.02
0.90	0.04	1.02	1.02
1.00	0.05	1.02	1.03
2.00	0.06	1.04	1.04
3.00	0.07	1.05	1.05
4.00	0.07	1.03	1.03
5.00	0.08	1.02	1.01
6.00	0.09	1.03	1.03
7.00	0.09	1.05	1.06
8.00	0.10	1.09	1.10
9.00	0.12	1.12	1.13
10.00	0.12	1.13	1.14
11.00	0.13	1.13	1.14
12.00	0.13	1.10	1.11
13.00	0.12	1.05	1.06
14.00	0.13	1.03	1.04
15.00	0.14	1.09	1.09
16.00	0.16	1.14	1.14
17.00	0.17	1.17	1.17
18.00	0.18	1.19	1.18
19.00	0.19	1.18	1.17
20.00	0.19	1.16	1.14
21.00	0.18	1.11	1.10
22.00	0.18	1.07	1.06
23.00	0.18	1.05	1.04
24.00	0.19	1.04	1.03
25.00	0.19	1.03	1.03
26.00	0.20	1.06	1.07
27.00	0.21	1.12	1.12
28.00	0.22	1.14	1.14
29.00	0.22	1.15	1.16
30.00	0.23	1.16	1.16
31.00	0.23	1.11	1.11
32.00	0.22	1.05	1.05
33.00	0.23	1.04	1.04



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS

REV. OR  
 KMR-35M+  
 12/5/2025  
 Page 1 of 1