

Adapter, N-Female Quick-Connect to N-Male**NF-MQK50+***Typical Performance Data*

FREQ.	INSERTION LOSS	N-FEMALE VSWR	N-MALE VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.00	1.01	1.01
0.10	0.01	1.00	1.00
0.20	0.02	1.01	1.01
0.30	0.03	1.01	1.01
0.40	0.04	1.01	1.01
0.50	0.04	1.01	1.01
1.00	0.05	1.02	1.01
1.50	0.05	1.02	1.00
2.00	0.07	1.02	1.01
2.50	0.06	1.02	1.01
3.00	0.07	1.02	1.01
3.50	0.07	1.03	1.03
4.00	0.07	1.04	1.05
4.50	0.08	1.05	1.05
5.00	0.08	1.06	1.04
5.50	0.09	1.07	1.06
6.00	0.09	1.06	1.10
6.50	0.07	1.05	1.10
7.00	0.06	1.04	1.08
7.50	0.07	1.04	1.09
8.00	0.07	1.04	1.10
8.50	0.10	1.06	1.08
9.00	0.09	1.09	1.08
9.50	0.10	1.09	1.10
10.00	0.10	1.10	1.09
10.50	0.09	1.09	1.07
11.00	0.09	1.08	1.03
11.50	0.11	1.06	1.02
12.00	0.08	1.08	1.05
12.40	0.08	1.11	1.08



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: www.minicircuits.com

IF/RF MICROWAVE COMPONENTS

REV. OR
NF-MQK50+
10/21/2025
Page 1 of 1