

# Adaptor SMA-Male to SMA-Male

# SM-SM50-27+

## Typical Performance Data

FREQ.	INSERTION LOSS	SMA-Male VSWR	SMA-Male VSWR
(GHz)	(dB)	(:1)	(:1)
0.01	0.01	1.01	1.01
0.2	0.02	1.01	1.01
0.4	0.03	1.01	1.01
0.6	0.03	1.01	1.01
0.8	0.03	1.01	1.01
1.0	0.03	1.01	1.01
2.0	0.04	1.01	1.01
3.0	0.04	1.01	1.01
4.0	0.04	1.02	1.02
5.0	0.04	1.03	1.03
6.0	0.05	1.05	1.05
7.0	0.05	1.06	1.06
8.0	0.05	1.08	1.08
9.0	0.06	1.08	1.08
10.0	0.05	1.08	1.08
11.0	0.05	1.07	1.06
12.0	0.05	1.04	1.03
13.0	0.05	1.01	1.01
14.0	0.05	1.02	1.03
15.0	0.06	1.04	1.04
16.0	0.06	1.05	1.05
17.0	0.06	1.05	1.06
18.0	0.07	1.04	1.04
19.0	0.07	1.02	1.01
20.0	0.07	1.04	1.03
21.0	0.07	1.06	1.05
22.0	0.08	1.08	1.06
23.0	0.08	1.10	1.09
24.0	0.08	1.10	1.08
25.0	0.07	1.06	1.05
26.0	0.06	1.02	1.02
26.5	0.07	1.03	1.02



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site  
 The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)



IF/RF MICROWAVE COMPONENTS