

# Armored Flexible Cable 1.0 mm Female to 1.0 mm Female

# WBL-0.5FT-W1F+

## Typical Performance Data

FREQ.	INSERTION LOSS	1.0 mm FEMALE RETURN LOSS	1.0 mm FEMALE RETURN LOSS
(MHz)	(dB)	(dB)	(dB)
0	0.02	46.66	51.01
1	0.20	30.69	30.49
3	0.44	26.26	26.05
7	0.64	38.67	38.50
11	0.79	24.17	24.33
15	0.88	31.78	32.95
19	0.98	35.65	33.71
23	1.07	30.15	29.84
27	1.16	33.94	33.34
31	1.24	34.82	35.49
35	1.35	25.47	25.38
39	1.44	26.84	26.85
43	1.58	18.62	18.82
47	1.62	26.96	26.54
51	1.70	28.59	28.03
55	1.84	20.96	20.20
59	1.93	18.87	18.10
63	1.96	25.26	26.33
67	2.02	30.48	32.28
71	2.12	28.06	27.70
75	2.20	25.54	26.42
79	2.27	29.29	28.39
83	2.34	29.20	30.18
87	2.44	25.29	25.67
91	2.56	24.04	23.25
95	2.56	26.61	27.63
99	2.62	28.00	27.49
103	2.76	23.89	22.74
107	2.83	24.06	23.62
110	2.91	25.00	24.34



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)

IF/RF MICROWAVE COMPONENTS

REV. OR  
WBL-0.5FT-W1F+  
11/15/2024  
Page 1 of 1