

# Armored Flexible Cable 1.0 mm Male to 1.0 mm Male

# WBL-0.5FT-W1M+

## Typical Performance Data

FREQ.	INSERTION LOSS	1.0 mm MALE RETURN LOSS	1.0 mm MALE RETURN LOSS
(GHz)	(dB)	(dB)	(dB)
0	0.02	44.55	45.87
1	0.20	32.31	32.50
3	0.43	29.48	28.97
7	0.65	39.57	38.67
11	0.78	31.51	32.40
15	0.88	30.39	30.30
19	0.98	35.32	34.74
23	1.07	36.16	34.65
27	1.16	36.28	33.06
31	1.26	30.67	33.45
35	1.35	30.76	30.40
39	1.45	26.33	27.70
43	1.55	23.24	25.11
47	1.64	23.96	24.93
51	1.70	31.80	31.30
55	1.77	31.99	30.69
59	1.86	28.42	27.95
63	1.93	30.14	30.67
67	1.99	31.21	31.87
71	2.09	30.35	31.32
75	2.19	23.56	25.14
79	2.30	23.68	27.71
83	2.36	22.17	21.33
87	2.42	30.26	25.85
91	2.58	28.39	25.06
95	2.59	21.18	24.63
99	2.72	22.22	20.94
103	2.76	24.12	21.24
107	2.82	29.23	26.39
110	2.91	24.64	26.03



P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 • Fax (718) 332-4661 For detailed performance specs & shopping online see Mini-Circuits web site



The Design Engineers Search Engine Provides ACTUAL Data Instantly From MINI-CIRCUITS At: [www.minicircuits.com](http://www.minicircuits.com)

IF/RF MICROWAVE COMPONENTS

REV. OR  
WBL-0.5FT-W1M+  
11/22/2024  
Page 1 of 1