

Phase-Stable Flexible Cable N-Type Male to N-Type Male

CBN-1FT-NMNM+

Typical Performance Data

FREQ.	INSERTION LOSS	N-TYPE MALE RETURN LOSS IN	N-TYPE MALE RETURN LOSS OUT
(GHz)	(dB)	(dB)	(dB)
0	0.02	45.51	43.18
1	0.13	43.98	50.90
2	0.19	33.07	33.19
3	0.22	44.38	41.87
4	0.25	39.39	37.46
5	0.30	31.28	28.87
6	0.31	32.57	38.01
7	0.33	30.13	30.76
8	0.31	28.40	27.31
9	0.31	29.06	28.58
10	0.29	34.74	31.45
11	0.29	35.80	37.91
12	0.31	30.65	28.53
13	0.33	31.42	30.86
14	0.29	36.86	25.73
15	0.31	27.05	25.55
16	0.38	21.26	22.47
17	0.30	30.47	31.03
18	0.30	34.25	33.43