

Armored Flexible Cable 1.0 mm Female to 1.0 mm Male

WBL-0.5FTW1F1M+

Typical Performance Data

FREQ.	INSERTION LOSS	1.0 mm MALE RETURN LOSS	1.0 mm FEMALE RETURN LOSS
(GHz)	(dB)	(dB)	(dB)
0	0.03	51.87	51.61
1	0.20	32.54	32.80
3	0.42	29.21	28.93
7	0.62	42.45	42.32
11	0.75	27.94	31.39
15	0.87	35.41	32.60
19	1.01	31.73	31.19
23	1.09	28.78	29.31
27	1.17	28.72	28.34
31	1.26	27.76	28.45
35	1.36	25.35	28.50
39	1.46	22.76	23.99
43	1.52	27.92	28.41
47	1.63	24.48	23.88
51	1.73	26.51	28.31
55	1.85	18.47	19.71
59	1.91	21.09	25.32
63	1.96	25.26	25.92
67	2.02	26.89	26.62
71	2.11	23.49	25.43
75	2.20	28.68	28.12
79	2.28	25.88	22.75
83	2.36	30.57	21.06
87	2.44	21.18	22.59
91	2.58	23.48	27.34
95	2.55	28.20	20.56
99	2.67	23.78	20.83
103	2.71	26.63	22.75
107	2.79	27.45	28.08
110	2.90	24.88	28.29

