

Armored Flexible Cable 1.0 mm Male to 1.0 mm Female

WBL-1FT-W1F1M+

Typical Performance Data

FREQ.	INSERTION LOSS	1.0 mm MALE RETURN LOSS	1.0 mm FEMALE RETURN LOSS
(GHz)	(dB)	(dB)	(dB)
0	0.04	46.83	46.83
1	0.33	31.39	31.76
3	0.71	43.70	39.46
7	1.07	37.46	42.19
11	1.31	40.30	42.94
15	1.53	35.13	36.59
19	1.75	29.33	36.69
23	1.92	29.99	34.72
27	2.08	36.40	34.12
31	2.26	27.85	30.85
35	2.42	24.15	28.52
39	2.58	25.89	27.52
43	2.71	39.55	26.83
47	2.90	24.69	24.14
51	3.09	19.56	20.71
55	3.22	19.89	21.28
59	3.32	24.17	25.11
63	3.46	27.18	25.11
67	3.59	23.05	24.62
71	3.72	24.60	23.51
75	3.88	30.31	20.97
79	4.02	28.60	19.28
83	4.19	22.04	17.86
87	4.27	23.00	22.67
91	4.47	24.15	23.37
95	4.54	20.78	17.03
99	4.71	22.90	18.64
103	4.79	30.51	22.07
107	4.91	27.05	27.22
110	5.15	18.30	19.40

