

Bias-Tee, Coaxial ZBT-243-1A-FT+

Typical Performance Data

FREQUENCY (GHz)	INSERTION LOSS (dB)	RETURN LOSS (dB)	
		INPUT	OUTPUT
0.01	-1.71	13.3	12.4
0.1	-0.90	16.4	16.1
0.5	-0.18	32.6	29.7
1.0	-0.32	34.8	29.2
2.0	-0.45	26.0	24.3
3.0	-0.49	20.7	20.7
4.0	-0.53	18.4	18.9
5.0	-0.55	16.6	16.5
6.0	-0.60	15.6	15.4
7.0	-0.61	14.8	14.7
8.0	-0.67	15.1	15.0
9.0	-0.66	15.8	15.5
10.0	-0.65	16.5	16.0
11.0	-0.67	16.0	15.4
12.0	-0.74	14.7	14.2
13.0	-0.82	13.4	12.6
14.0	-0.89	13.2	11.9
15.0	-0.92	14.4	12.3
16.0	-1.00	15.7	12.8
17.0	-1.12	15.5	12.9
18.0	-1.18	16.8	13.7
19.0	-1.19	20.6	17.1
20.0	-1.29	18.8	20.6
21.0	-1.45	15.7	20.0
22.0	-1.56	15.4	20.4
23.0	-1.65	16.3	23.4
24.0	-1.79	16.1	22.8